



HCS0905AC

Product code: HCS0905AC

Manufacturer: JL World

HCS0905AC is a JL World electromagnetic buzzer, SMD mounting type.

Features:

Dimensions: Ø9.0x3.2 mm

Rated Voltage: 5 V

Operating Voltage: 4 ~ 6 V

Rated Frequency: 2730 Hz

Rated Current: ≤ 80 mA

SPL (sound pressure level) at 10cm: ≥ 85 dB

Coil Resistance (Ω)	30 ± 3
Rated Current (mA)	≤80
Rated Frequency (Hz)	2730
SPL at 10 cm (dB)	≥ 85
Technology	Electro-Magnetic
Operating temperature	-40 ~ +85
Operating Voltage (V)	4~6
Typology	SMD