



HCS0503K

Product code: HCS0503K

Manufacturer: JL World

HCS0503K is a JL World electromagnetic buzzer, SMD mounting type.

Features:

Dimensions: 5x5x2.5 mm

Rated Voltage: 3 V

Operating Voltage: 2 ~ 4 V

Rated Frequency: 4000 Hz

Rated Current: ≤ 110 mA

SPL (sound pressure level) at 10cm: ≥ 75 dB

Coil Resistance (Ω)	12 ± 3
Rated Current (mA)	≤ 110
Rated Frequency (Hz)	4000
SPL at 10 cm (dB)	≥ 75
Technology	Electro-Magnetic
Operating temperature	-40 ~ +85
Operating Voltage (V)	2~4
Typology	SMD