



HCS0805D

Product code: HCS0805D

Manufacturer: JL World

HCS0805D is a JL World electromagnetic buzzer, SMD mounting type.

Features:

Dimensions: 7.5x7.5x2.5 mm

Rated Voltage: 5 V

Operating Voltage: 4 ~ 7 V

Rated Frequency: 2900 Hz

Rated Current: ≤ 120 mA

SPL (sound pressure level) at 10cm: ≥ 85 dB

Coil Resistance (Ω)	30 ± 3
Rated Current (mA)	≤ 120
Rated Frequency (Hz)	2900
SPL at 10 cm (dB)	≥ 85
Technology	Electro-Magnetic
Operating temperature	-40 ~ +85
Operating Voltage (V)	4~7
Typology	SMD