



HCS1206AX

Product code: HCS1206AX

Manufacturer: JL World

HCS1206AX is a JL World electromagnetic buzzer, SMD (self drive) mounting type.

Features:

Dimensions: 12.8x12.8x10 mm

Rated Voltage: 6 V

Operating Voltage: 4 ~ 8 V

Rated Frequency: 2300±300 Hz

Rated Current: ≤ 30 mA

SPL (sound pressure level) at 10cm: ≥ 85 dB

Rated Current (mA)	≤30
Rated Frequency (Hz)	2300±300
SPL at 10 cm (dB)	≥85
Technology	Electro-Magnetic
Operating temperature	-40 ~ +85
Operating Voltage (V)	4~8
Typology	SMD (Self Drive)